CH-5PPS

5 Pin Caravan - Trailer Plug & Socket Kit



This kit is suitable for use with 4 core Chipatronic Caravan Cabling using Aopulo fittings but can be used for any electrical automotive connection.
The terminations require solder connections which should be carried out by installer.

Suitable for low voltage only. Not to be used for any other application.

Installation Instructions

For 4 core camera cable

- Loosen the grub screw enough to undo the backshell and remove this.
- Undo the cable gland and insert cable through.
- Strip about 30mm of outer insulation from cable and then 2-3mm from wires to expose the copper.
- Tin the bare copper wires with solder.
- Tin the terminals with solder.
- Solder the wires to the terminals as per the pin definition.
- Re-assemble, tighten grub screw and gland carefully. Do not twist cable.
- Repeat process for the second part, note that terminals will be reversed.







Pin Definition for Standard Video System

1. Yellow = Video
2. Red = Power (+)
3. White = Audio or Video #2
4. Black = Ground (-) This may be wire screen
5. Not used for standard camera system

